

## SCD7500Q



**ATS si AVR  
inclus**



1 x priza 16 Ah  
1 x priza 32 Ah

| Generator Senci            | SCD7500Q        |
|----------------------------|-----------------|
| Plaja tensiune             | 230-235 V       |
| Plaja frecventa            | 50-55 Hz        |
| Putere max. 230V           | <b>6.0 kVA</b>  |
| Putere in regim continuu   | <b>5.0 kVA</b>  |
| Amperaj                    | 8.3 A           |
| Regulator de tensiune      | AVR             |
| Tip motor                  | Senci 188FE     |
| Putere motor Senci         | 13 cp           |
| Turatie motor              | 3000 rpm        |
| Factor de putere           | 1.0             |
| Demaraj electric           | Echipe standard |
| Racire                     | Aer             |
| Carburant                  | Motorina        |
| Capacitate rezervor        | 18.0 l          |
| Consum                     | ≤ 2.3 l/h       |
| Autonomie (100% putere)    | ≤ 7.5 ore       |
| Nivel zgomot (100% putere) | 70-74 DbA       |
| Greutate utilaj            | 170 kg          |
| Dimensiuni LxIxh (mm)      | 960x560x770     |

### Echipe standard:

Contor ore, voltmetru si frecventa  
Alternator Senci de calitate superioara  
Alerta nivel ulei scazut cu oprire automata a motorului  
Senzor de suprasarcina cu auto-oprire  
Silentios si prietenos cu mediul  
Regulator de tensiune AVR  
Compact, cadru rezistent  
Performanta chiar si dupa 13 ore de functionare continua  
la o sarcina de 50% pentru uz casnic dar si comercial  
Panou de control rezistent la ploaie si praf  
Intrerupator circuit ce opreste alimentarea atunci cand  
sistemul este suprasolicitat  
Echiptat cu roti pentru o mai buna deplasare  
Rezervor combustibil de 18.0 litri



[www.italiastar.ro](http://www.italiastar.ro)



Italia Star Com Due S.R.L.  
Autostrada București - Pitești km. 13.2  
Loc. Chiajna - Ilfov  
Tel: 021.433.03.27  
Fax: 021.433.03.26  
[info@italiastar.ro](mailto:info@italiastar.ro) [www.italiastar.ro](http://www.italiastar.ro)